



[English]

Configure your camera part:

1. Download and install the "Idinio" app from the Apple App Store or Google Play Store on your mobile device.
2. Activate the "Idinio" app.
3. Create a new account or log in to your existing account.
4. Click on "+" to add the product. (add an App snapshot?)
5. Select the product category "Camera".
6. Select the product ""View dong"
7. Power on camera part with supplied cable to a 5VDC 1.0A USB port
8. Setup the camera part ready to be connected
 - a. If the status indicator is not flashing in red, press the reset* button for 10 seconds.
 - b. If the status indicator is flashing in red, it is ready to start connecting.
9. Confirm in APP to start the connecting.
10. Confirm in APP with right Wi-Fi network and password.
11. Scan the QR code in the App with the camera. The product gives confirmation sound. Then the status indicator will turn to blue and flashing.
12. When connection is done, the status indicator will be blue, solid on.
13. Confirm in APP with "Heard the beep"
14. Change the name of View dong if you want.
15. USB bell configure dialogue will show up, choose "Wireless bell"
16. Now you have finish configuring the camera part. You should be able to see real time video from the camera.
17. If you failed in the middle, please always start from step 8 again.

Configure your USB bell:

1. Go to main menu of View dong, choose "Settings"
2. Choose "Bell setting", make sure you select "Wireless bell"
3. Press the "reset" button once and short on the back side of USB bell, the indicator on the bell will be blue and flashing.
4. Go to main menu of View dong, choose "Settings"
5. Choose "Ring Setup"
6. Down below this page, you can "Remove binding" or "Add"
7. When you click "Add", the USB bell should be connected and the indicator on the bell will be steady blue.
8. Now you can use your USB bell, on this page you can also choose different ring tones.
9. If you failed in the middle, please always starts from step 1.



[Nederlands]

Configureer uw camera:

1. Download en installeer de app "Idinio" van de Apple App Store of Google Play Store op uw mobiele apparaat.
2. Start de app "Idinio".
3. Maak een nieuw account of log in op uw bestaande account.
4. Klik op "+" om het product toe te voegen.
5. Selecteer de productcategorie "Camera".
6. Selecteer het product "" View dong "
7. Schakel het cameragedeelte in met de meegeleverde kabel naar een 5VDC 1.0A USB-poort
8. Status van de camera:
 - a. Als de statusindicator niet rood knippert, drukt u 10 seconden op de knop reset.
 - b. Als de statusindicator rood knippert, is deze klaar om verbinding te maken.
9. Bevestig in de APP om het verbinden te starten.
10. Bevestig in de APP het juiste wifi-netwerk en wachtwoord.
11. Scan de QR-code in de app met de camera door de QR-code in het scherm van uw telefoon voor de camera te houden. Het product geeft een bevestigingsgeluid. Vervolgens wordt de statusindicator blauw en knippert deze.
12. Als de verbinding tot stand is gebracht, is de statusindicator blauw en blijft deze branden.
13. Bevestig in de APP met "Hoorde de piep"
14. Wijzig desgewenst de naam van View dong.
15. USB bell configureren dialoog verschijnt, kies "Wireless bell"
16. Nu bent u klaar met het configureren van de camera. U zou realtime video van de camera moeten kunnen zien.
17. Wanneer de installatie faalt, controleer de werking van uw WiFi netwerk herhaal de installatie vanaf stap 8a.

Configureer uw USB bel:

1. Ga naar het hoofdmenu van View dong, kies "Instellingen" (rechtsboven).
2. Kies "Bel instellingen", zorg ervoor dat u "Wireless bell" selecteert
3. Druk één keer kort op de knop "reset" aan de achterkant van de USB-bel, de indicator op de bel is blauw en knippert.
4. Ga naar het hoofdmenu van View dong, kies "Instellingen"
5. Kies "Beltooninstellingen"
6. Onderaan deze pagina kunt u "Binding verwijderen" of "Toevoegen"
7. Wanneer u op "Toevoegen" klikt, moet de USB-bel worden aangesloten en zal de indicator op de bel constant blauw branden.
8. Nu kunt u uw USB-bel gebruiken, op deze pagina kunt u ook verschillende beltonen kiezen.
9. Wanneer de installatie niet lukt, controleer de werking van uw WiFi netwerk herhaal de installatie vanaf stap 1.